

## PRODUCT DATA SHEET

### BRIGHTER AIR DMX

Brighter Air DMX is a 512 DMX channels transmitter/receiver. Air DMX provides reliable wireless DMX transmission, compatible with the W-DMX protocol. The device is equipped with 3-pin and 5-pin DMX sockets and large display for quick and intuitive operation. Everything closed in small compact housing.

#### **Electrical Parameters:**

**Maximum Power Consumption:** 30W

**Power Supply Voltage:** 9V DC

#### **Features and Functions:**

**Operating Modes:** TX/RX/Auto

**Communication protocols:** W-DMX G5, W-DMX G4S, W-DMX G3

**Up to 85 devices in auto mode**

**Operation band:** 2,4GHz

**Thread** 1/4 inch

**DC Power supply**

#### **Physical Parameters:**

**Protection Level:** IP20

**Dimensions:** 160x160x130mm

**Weight:** 1 kg

**Power Supply Sockets Standard:** DC

**DMX Sockets:** 3-pin and 5-pin

The above-mentioned device, which is the subject of this product specification, complies with the relevant requirements of Union harmonization legislation.

EN 55015:2013

EN 61547:2009

EN 61000-3-2:2006+A1:2009+A2:2009

EN 61000-3-3:2013